

Power

Cordex™ CXC

125/220V Rackmount System Controller



CXCR

- LCD touch-screen user interface
- Internet ready, integrated SNMP
- High reliability CAN bus communication
- User definable alarms
- Flexible battery management features
- Smart peripheral features

Cordex CXC brings advanced technology to the DC power industry. This compact system controller is designed for seamless operation and set up of Argus power systems and is equipped with a complete range of features.

A graphic LCD display with a state-of-the-art touch-screen interface allows simple and convenient local set up, control, and monitoring of Cordex rectifiers. By utilizing TCP/IP technology, complete configuration and monitoring of power equipment is possible through a network web browser.

The Cordex CXC system controller ensures effortless operation of the Cordex rectifier family. Time consuming, complicated set up and monitoring of DC power systems or smart peripheral modules is now a thing of the past.

Cordex CXC System Controller

Features

User Interface

GUI:	Use internet browser (IE6 and above) to access embedded GUI through Ethernet port or RS-232 craft port
Display:	Full graphic LCD, 160 x 160 pixels, with backlight and contrast adjustment
LED indicators:	System OK—Green Minor alarm—Yellow Major alarm—Red
Controls:	LCD touch screen with virtual alpha numeric and numeric keyboards
Audio:	Built in speaker for alarms and popup messages
Language:	Multi language support including Chinese characters

Communication Ports

RS-232 port:	Craft port on front panel for local connection and optional 2 nd port on rear panel for remote connection via external modem series
CAN:	Interface to Cordex series rectifiers and optional smart peripheral modules
Ethernet:	10/100 Base T with half/full duplex
Modem:	Optional internal or external modems with dial back security and password control

Alarm

Relays:	Potential free Form C contacts
SNMP:	Compatible with HP Openview, SNMPc
Pager:	Via modem

Data Logging

Daily statistics:	Minimum, maximum and average on analog input channels, with date and time stamp Battery current, rectifier current, and AC mains voltage for last 90 days
Event log:	On all events such as alarms, power on, any change of state of the digital inputs, or other miscellaneous events
Battery log:	Battery health history on last 20 discharges, time of discharge, and battery capacity

Control Functions:

Battery temperature compensation
Automatic, scheduled (periodic) or manual equalize
Automatically terminated equalize charge
Battery current terminate equalize
Dynamic charge current control
Multiple LVD controls
Battery capacity and runtime prediction
Battery mid-point monitoring
Auto or manual battery test

Smart Peripheral Modules

Shunt multiplexer:	Monitors up to 16 shunts per module
Battery cell monitor:	1 string of 2V cells or 4 strings of 12V cells per module

Electrical

Input voltage:	90 to 300VDC
Power consumption:	5W
Ground fault detection:	0 to 10mA

Mechanical

Mounting:	CXCR with 19" or 23" rack mounting CXCP panel mount
-----------	--

Dimensions

CXCP/R (Plus 19" or 23" bracket)	
mm:	131H x 431W x 100D
inches:	5.1H x 16.9W x 3.9D

Weight

CXCP/R	6.2kg (13.8lb)
--------	----------------

Environmental

Temperature	
Extended:	-40 to 65°C (-40 to 149°F)
Humidity:	0 to 95% RH non-condensing

Standards

Safety:	CSA/UL 60950-1-03
Emissions:	CFR47 (FCC) Part 15 Class A FCC Part 68 ICES-03 Class A CE mark EN55022 (CISPR 22) Class A C-tick (Australia)
Immunity:	EN 61000-4-2 EN 61000-4-3 EN 61000-4-4 EN 61000-4-5 EN 61000-4-6

For contact information visit www.alpha.com

The Alpha Group >	Europe, Middle East & Africa	Asia Pacific	North America	Latin & South America	
	Cyprus Tel: +357 25 375 675 Fax: +357 25 359 595 South Africa Tel: +27 11 608 1936 Fax: +27 11 608 1948	Germany Tel: +49 9122 79889 0 Fax: +49 9122 79889 21 United Kingdom Tel: +44 1279 501110 Fax: +44 1279 659870	Russia Tel: +7 495 916 1854 Fax: +7 495 916 1349 P.R. China Tel: +86 769 533 2600 Fax: +86 769 532 6603	Canada Tel: +1 604 436 5900 Fax: +1 604 436 1233 USA Tel: +1 360 671 7054 Fax: +1 360 671 7096	Mexico Tel: +52 55 5280 6990 Fax: +52 55 5280 6585